

IQ2015™ Connectivity Test System



General Technical Specifications

Analyzer

Parameter	Port Designations	Range
Input frequency range	NFC ports - DIG1, DIG2	DC to 30 MHz
	FM port	76 to 108 MHz
Input power range	RF1 / RF2 ports	2150 - 2700 MHz 3300 - 3800 MHz 4900 - 6000 MHz
	NFC ports - DIG1, DIG2	Up to 1000 mV RMS
	FM port	+10 to -40 dBm
	RF1 / RF2 ports	+30 to -148 dBm/Hz
Control interface		USB 2.0 type B
Power requirements		100-240 VAC, < 300 W, 50-60 Hz
Phase noise		< -110 dBc/Hz (250 kHz to 400 kHz offset)

Analyzer — Signal Trigger

Parameter	Range
Absolute minimum value	-40 dBm
Absolute maximum value	Limited by the maximum input power
Accuracy	< +/- 2 dB

Generator

Parameter	Port Designations	Range
Output frequency range	NFC ports - DIG1, DIG2	DC to 35 MHz
	FM port	76 to 108 MHz
	RF1 / RF2 ports	2150 - 2700 MHz 3300 - 3800 MHz 4900 - 6000 MHz
	GPS, GLONASS port	1.57542 GHz (fixed)
Output power range	NFC ports - DIG1, DIG2	5 to 1000 mV RMS
	FM port	-60 to -110 dBm
	RF1 / RF2 ports (CW)	+10 to -95 dBm (1 Hz BW)
	GPS, GLONASS port	-60 to -145 dBm

Timebase

Oscillator type	OCXO
Frequency	10MHz
Initial accuracy (25°C after 60 min. warm-up)	< +/- 0.05ppm
Maximum aging	< +/- 0.1ppm per year
Temperature stability	< +/-0.05ppm over 0oC to 50°C range, referenced to 25°C
Warm-up time (to within +/-0.1ppm at 25°C)	< 30 minutes

Wireless LAN (802.11 a/b/g/n/j) Hardware Technical Specifications

Analyzer

Input frequency range	2400 - 2500 MHz 4900 - 6000 MHz
Input power range	+30 to -148 dBm/Hz
Measurement bandwidth	60 MHz (\pm 30 MHz quadrature)
Quantization	14 bits
Input return loss	> 10 dB
Spurious	< -55 dBc (50 kHz RBW)
Harmonics	Out-of-band: \leq -45 dB In-band: \leq -55 dB (100 kHz resolution BW)
Integrated phase noise	< 0.5 degrees ($f < 2.5$ GHz) < 0.8 degrees ($f < 6$ GHz) 0.5 degrees (100 Hz – 1 MHz) (typical)
Signal to noise ratio	\geq 55 dB (measured in 100 kHz resolution bandwidth)
Waveform capture duration	400 ms

Generator

Output frequency range	2400 - 2500 MHz 4900 - 6000 MHz
Output power range	-95 to 0 dBm (modulated) -95 to +10 dBm (CW)
Output power accuracy	± 1.0 dB (+ 5 to -95 dBm) ± 0.5 dB typical
Signal bandwidth	70 MHz (± 35 MHz quadrature)
Quantization	14 bits
Output return loss	> 10 dB
Spurious	Specification: ≤ -20 dBc out-of-band (harmonics, to 0 dBm output level) ≤ -35 dBc or ≤ -80 dBm (whichever is higher) out-of-band (non-harmonic) Typical: ≤ -50 dBc (in-band)
Harmonics	Out-of-band: ≤ -45 dB in-band: ≤ -55 dB (100 kHz resolution BW)
Integrated phase noise	< 0.5 degrees (100 Hz – 1 MHz) (typical)
Signal to noise ratio	≥ 55 dB (measured in 100 kHz resolution bandwidth) (specification) ≥ 70 dB (measured in 100 kHz resolution bandwidth) (typical)
Carrier leakage	≤ -45 dBc (CW output) ≤ -90 dBm (between packets, when enhanced gap rejection condition enabled)
Waveform duration	400 ms

Wireless LAN (802.11 a/b/g/n/j) Measurement Specifications

Measurement	Description	Performance
EVM	All: EVM averaged over all symbols and all subcarriers (dB) 802.11a/g/n/j OFDM signals only	Residual VSA EVM: ≤ -35 dB (1.78%) (-5 dBm to -35 dBm) ≤ -41 dB (0.89%) typical Residual VSG EVM: ≤ -38 dB (-95 to -10 dBm output power) ≤ -35 dB (-10 to -5 dBm output power)
	Data: EVM averaged over all symbols and all subcarriers (dB) 802.11a/g/n/j OFDM signals only	
	Pilots: EVM averaged over all symbols and all subcarriers (dB) 802.11a/g/n/j OFDM signals only	
	PSDA EVM average: EVM averaged over all PSDU data symbols (or, if "11b std Tx mod acc" is selected, over last 1000 chips) (dB) 802.11b/g DSSS signals only	
	PSDA EVM average peak: EVM value (dB) 802.11b/g DSSS signals only	
Peak power	Peak power over all symbols (dBm)	
RMS power	All: average power of complete data capture (dBm)	± 1.0 dB (specification) ± 0.5 dB (typical)
	No gap: average power over all symbols after removal of any gap between packets (dBm)	
Max avg power	Peak value of the amplitude as a moving average over 40 samples (dBm)	
I/Q amplitude error	I/Q amplitude imbalance (%) and approximate contribution to EVM (dB)	
I/Q phase error	I/Q phase imbalance (degrees) and approximate contribution to EVM (dB)	
Frequency error	Carrier frequency error (kHz)	
Symbol clock error	Symbol clock frequency error (ppm)	
RMS phase noise	Integrated phase noise (degrees)	
PSD	Power spectral density (dBm/Hz) versus frequency offset Center frequency ± 40 MHz LitePoint API produces 1024-point FFT	
Spectral flatness	Reflects variation of signal energy as a function of OFDM subcarrier number 802.11a/g OFDM signals only	
CCDF (complementary cumulative distribution function)	Probability of peak signal power being greater than a given power level versus peak-to-average power ratio (dB)	

Measurement	Description	Performance
Power on / power down ramp	On: relative power level (% of average) versus time (802.11b/g CCK signals only) Power-on time from 10% to 90% Power-on time from 90% power level to start of packet (Not provided for 802.11a/g/j OFDM signals)	
	Off: Relative power level (% of average) versus time (802.11b/g CCK signals only) Power-off time from 90% to 10% (not reliable for 802.11a/g/j OFDM signals) Power-off time from _ 90% power level to detected end of packet (not provided for 802.11a/g OFDM signals)	
Eye diagram	I and Q channels versus time (802.11b/g DSSS signals only)	
PSDU data	Recovered binary data sequence, including the MAC header and Frame Check Sequence, if present	
Raw capture data	I and Q signals versus time	
General waveform analysis	DC offset, RMS level, minimum/maximum amplitude, peak-to-peak amplitude, RMS I- and Q-channel levels	
CW frequency analysis	Frequency of CW tone	

Bluetooth (1.0, 2.0, 2.1, 3.0, 4.0) Hardware Technical Specifications

Analyzer

Input frequency range	2400 - 2500 MHz
Input power range	+30 to -148 dBm (1 Hz BW)
Measurement bandwidth	60 MHz (\pm 30 MHz quadrature)
Quantization	14 bits
Input return loss	> 10 dB
Spurious	< -55 dBc (50 kHz RBW)
Harmonics	Out-of-band: \leq -45 dB In-band: \leq -55 dB (100 kHz resolution BW)
Integrated phase noise	0.5 degrees (100 Hz – 1 MHz) (typical)
Signal to noise ratio	\geq 55 dB (measured in 100 kHz resolution bandwidth)
Power measurement accuracy	\pm 1.0 dB (specification) \pm 0.5 dB (typical)
Waveform capture duration	400 ms

Generator

Output frequency range	2400 - 2500 MHz
Output power range	-95 to 0 dBm (modulated) -95 to +10 dBm (CW)
Signal bandwidth	70 MHz (\pm 35 MHz quadrature)
Quantization	14 bits
Output return loss	> 10 dB
Spurious	Specification: \leq -50 dBc (in-band) Typical: \leq -20 dBc out-of-band (harmonics, to 0 dBm output level) \leq -35 dBc or \leq -80 dBm (whichever is higher) out-of-band non-harmonic
Harmonics	Out-of-band: \leq -45 dB In-band: \leq -55 dB (100 kHz resolution BW)
Integrated phase noise	< 0.5 degrees ($f < 2.5$ GHz) < 0.8 degrees ($f < 6$ GHz) 0.5 degrees (100 Hz – 1 MHz) (typical)
Signal to noise ratio	\geq 55 dB (measured in 100 kHz resolution bandwidth) (specification) \geq 70 dB (measured in 100 kHz resolution bandwidth) (typical)
Carrier leakage	\leq -45 dBc (CW output) \leq -90 dBm (between packets, when enhanced gap rejection condition enabled)
Power accuracy	\pm 1.0 dB (specification) \pm 0.6 dB (typical)
Waveform duration	400 ms

Bluetooth (1.0, 2.0, 2.1, 3.0, 4.0) Measurement Specifications

Measurement	Description	Performance
TX output power	Transmit DUT output power (dBm)	VSA measure power accuracy: ± 1.0 dB (specification) ± 0.5 dB (typical)
TX output spectrum	Transmit DUT power spectral density	
20 dB bandwidth	Bandwidth between the +/- 20 dB down points of the modulation waveform	
In-band emissions (Adjacent Channel)	Spurious emission measured at +/- 5 MHz of DUT TX frequency only	
Modulation characteristics	Average and peak frequency deviation (Hz)	
Carrier frequency tolerance	Carrier frequency offset (Hz)	
Carrier frequency drift	Carrier frequency change over the Bluetooth burst (Hz)	
Relative transmit power (EDR)	Average power of complete data capture (dBm)	VSA measure power accuracy: ± 1.0 dB (specification) ± 0.5 dB (typical)
Carrier frequency stability (EDR)	Frequency drift over the Bluetooth EDR burst duration (Hz)	
Receive sensitivity	Receive sensitivity test using LitePoint or user-generated waveforms	Source power accuracy: ± 1.0 dB (specification) ± 0.6 dB (typical)
Maximum input signal level	Assuming single-ended BER measurement	
C/I and receiver selectivity performance	IQ2015 capability provides the wanted signal only. No interfering signal is available.	Residual VSA EVM: ≤ -35 dB (+20 to -25 dBm) Residual VSG EVM: ≤ -35 dB (-5 to -70 dBm)
Blocking performance	IQ2015 capability provides the wanted signal only. No interfering signal is available.	
Intermodulation performance	IQ2015 capability provides the wanted signal only. No interfering signal is available.	
Bit error rate (BER)	Bit error rate for 1 and 3 Mbps data rates	Source power accuracy: ± 1.0 dB (specification) ± 0.6 dB (typical)
RMS EVM (EDR)	RMS EVM for Bluetooth EDR	Residual VSA EVM: ≤ -30 dB (3.1%) (≥ -35 dBm power to + 10 dBm) Residual VSG EVM: ≤ -30 dB (3.1%) (≥ -35 dBm power to + 10 dBm)
Peak EVM (EDR)	Peak EVM for Bluetooth EDR	

WiMAX (802.16 d/e) Hardware Technical Specifications

Analyzer

Input frequency range	2150 - 2700 MHz 3300 - 3800 MHz 4900 - 6000 MHz
Input power range	+30 to -148 dBm/Hz
Measurement bandwidth	60 MHz (\pm 30 MHz quadrature)
Quantization	14 bits
Input return loss	> 10 dB
Spurious	< -55 dBc (50 kHz RBW)
Harmonics	Out-of-band: \leq -45 dB In-band: \leq -55 dB (100 kHz resolution BW)
Integrated phase noise	< 0.5 degrees (100 Hz – 1 MHz) (typical)
Signal to noise ratio	\geq 55 dB (measured in 100 kHz resolution bandwidth)
Waveform capture duration	400 ms

Generator

Output frequency range	2150 - 2700 MHz 3300 - 3800 MHz 4900 - 6000 MHz
Output power range	-95 to 0 dBm (modulated) -95 to +10 dBm (CW)
Signal bandwidth	70 MHz (\pm 35 MHz quadrature)
Quantization	14 bits
Output return loss	> 10 dB
Spurious	Specification: \leq -50 dBc (in-band) Typical: \leq -20 dBc out-of-band (harmonics, to 0 dBm output level) \leq -35 dBc or \leq -80 dBm (whichever is higher) out-of-band on-harmonic)
Harmonics	Out-of-band: \leq -45 dB In-band: \leq -55 dB (100 kHz resolution BW)
Integrated phase noise	0.5 degrees (100 Hz – 1 MHz) (typical)
Signal to noise ratio	\geq 55 dB (measured in 100 kHz resolution bandwidth) (specification) \geq 70 dB (measured in 100 kHz resolution bandwidth) (typical)
Carrier leakage	\leq -45 dBc (CW output) \leq -90 dBm (between packets, when enhanced gap rejection condition enabled)
Waveform duration	400 ms

WiMAX (802.16 d/e) Measurement Specifications

Measurement	Description	Performance
Power	Peak power: peak power over all symbols (dBm)	± 1.0 dB (specification) ± 0.5 dB (typical)
	Average power (all): average power of complete data capture (dBm)	
	Average power (no gap): average power over all symbols after removal of any gap between packets (dBm)	
	Average power (preamble): average preamble power (dBm)	
	Average power (syms): average power over all symbols, excluding preamble (dBm)	
EVM	EVM (all): EVM averaged over all symbols and all subcarriers (dB; %)	Residual VSA EVM: ≤ -40 dB (1.00%) (at ≥ -30 dBm to -10 dBm input) ≤ -46 dB (0.50%) typical Residual VSG EVM: ≤ -43 dB (>-30 dBm to -10 dBm output)
	EVM (data): EVM averaged over all symbols and all data subcarriers (dB; %)	
	EVM (pilots): EVM averaged over all symbols and all pilot subcarriers (dB; %)	
	EVM (unmod): EVM averaged over all un-modulated subcarriers (dB; %) (802.16e only)	
	EVM (carrier): Error Vector Magnitude averaged over all symbols for each subcarrier (dB) versus OFDM subcarrier number	
	EVM (time): Error Vector Magnitude averaged over all subcarriers (dB) versus time	
Capture mode	Selects one-shot or streaming data analysis (single / continuous)	
Sample interval	Sample interval time: 100 μs, 200 μs, 300 μs, 400 μs, 500 μs, 1 ms, 2 ms, 3 ms, 4 ms, 5 ms, 10 ms (The sample interval is limited by the 220 buffer size and 80 MHz A/D sample rate)	
Signal type	Automatically detected: Signal type (up- / downlink subframe), bandwidth, modulation / coding, Cyclic Prefix length (802.16d)	
	Automatically detected: signal type (up- / downlink subframe), bandwidth, modulation / coding, Cyclic Prefix length, Uplink fields. Supported modes: PUSC, FUSC, AMC2x3. The software can be set to do automatic detection of the up- and downlink maps, or these can be user-defined (GUI) (802.16e-2005 / WirelessMAN-OFDMA mobile WiMAX)	

Amplitude vs. Time	Instantaneous, and peak power averaged over a symbol duration (dBm) versus time	
Spectrogram	3D plot of power spectral density versus time. Time is displayed on x-axis; frequency offset on y-axis; color coding represents power (maximum strength is red; minimum strength is green)	
PSD	Power spectral density (dBm/Hz) versus frequency offset along with spectral mask per IEEE 802.16 for 10 and 20 MHz channels (scaled for other bandwidths) Resolution bandwidth 100 kHz (LitePoint API produces 1024-point FFT)	
Symbol constellation	Visual display of each demodulated symbol in the I/Q complex plane. The color of data symbols depends on stream; pilot tones are green. Shown for individual (selected) burst or all combined	
Spectral flatness	Variation from average energy as a function of OFDM subcarrier number (dB)	
Spectral delta	Power delta between adjacent subcarriers (dB)	
Phase noise (PSD)	Phase noise power spectral density (dBc/Hz) versus frequency offset	
Phase error (time)	Integrated phase error of pilot tones (degrees) versus time	
CCDF (complementary cumulative distribution function)	Probability of peak signal power being greater than a given power level versus peak-to-average power ratio (dB). Shown over all data or payload only.	
I & Q signals	I/Q signal voltages (Vrms) versus time	
I/Q phase error	I/Q phase imbalance (degrees)	
I/Q amplitude error	I/Q amplitude imbalance (%)	
Frequency error	frequency error (kHz) versus time	
LO (DC) leakage	Relative power to center carrier (dBc)	
CINR (preamble)	Carrier to Interference plus Noise Ratio (dB) of preamble	
CINR (data)	Carrier to Interference plus Noise Ratio (dB) of data zone	
OFDMA ranging	Ranging code and power level of initial and periodic ranging bursts (mobile WiMAX and if present only)	
Reed-Solomon Errors	Number of symbols with RS errors (valid only if payload decoding is enabled; fixed WiMAX only)	

WiMAX (802.16 d/e) Signal Settings

Measurement	Description	Performance
TX Mode	Selects continuous or specified number of packets to be transmitted (continuous / # packets (1 to 65,334))	
RF Channel	Center frequency of channel to be transmitted (MHz)	
CW Signal	Selects a CW signal to transmit	
Signal Level	Sets average power of transmitted signal (-98.0 dBm to 10.0 dBm with 0.1 dB resolution)	± 1.0 dB (specification) ± 0.6 dB (typical)
Transmit Trigger	Selects trigger mode (free run / external trigger)	
Gap Power Off	Sets transmitted power to minimum during gaps between data packets (On / Off)	
Signal Impairments	<ul style="list-style-type: none"> I/Q amplitude imbalance: -10.00% to +10.00% with resolution of 0.01% I/Q phase imbalance: -10.00 degrees to +10.00 degrees with resolution of 0.01 degrees I/Q group delay imbalance: -1.00 ns to +1.00 ns with resolution of 0.01 ns I-channel DC offset: -1.00 to +1.00 with resolution of 0.001 (units of Volts for baseband output; dBV for RF output) Q-channel DC offset: -1.00 to +1.00 with resolution of 0.001 (units of Volts for baseband output; dBV for RF output) 	

FM Hardware Technical Specifications

FM Analyzer

Parameter	Specification	Accuracy
Input Frequency Range	76 to 108 MHz	
Input Power Range	+10 to -40 dBm	± 1.0 dB (specification) ± 0.5 dB (typical)
Input Impedance	50 Ω	± 5%
Input Power Resolution	0.1 dB Step	
Input Deviation Range	1 k Hz to 100 kHz (10 Hz step)	
Frequency Accuracy	Same as Reference Timebase	
Harmonic Performance (in band, < +/- 100 kHz)	-65 dBc	
Harmonic Performance (out of band, > +/- 100 kHz)	-40 dBc	
Spurious (in band, < +/- 100 kHz)	-65 dBc	
Spurious (out of band, > +/- 100 kHz)	-40 dBc	

FM Generator

Parameter	Specification	Performance
Output Frequency Range	76 to 108 MHz	
Frequency Resolution	1 Hz	
Output Power Range	-40 to -110 dBm	± 1.0 dB (levels ≥ -100 dBm to -40 dBm)
Output Power Resolution	0.1 dB Step	
Output Impedance	50 Ω	±5%
FM Deviation Range	1 k Hz to 75 kHz	
FM Deviation Resolution	10 Hz	
Frequency Deviation Accuracy	+/- 3%	
AM Modulation Index	0 to 75%	
AM Modulation Frequency	0 to 1 MHz	
Phase Noise	-80 dBc/Hz at 10 kHz offset	
Harmonic Performance (in band)	-65 dBc	
Harmonic Performance (out of band)	-40 dBc	
Spurious (in band)	-60 dBc	
Spurious (out of band)	-40 dBc	
Modulation Accuracy	+/- 10 Hz	

FM Interference Source

Parameter	Specification	Notes
Interference Source	CW / Mono FM	
Interference Source Frequency Range	- 5 to 5 MHz	Relative to Carrier
Output Power Range	-30 dB to +40 dB	Relative to Carrier
Output Power Accuracy	+/- 1 dB	Relative to Carrier
Peak Deviation	1 kHz to 75 kHz (1 kHz resolution)	
Deviation Accuracy	100 Hz	
Number of Audio Tones	1	
Audio Frequency Range	200 Hz to 15 kHz in steps of 200 Hz	

Audio Analyzer

Audio Frequency Range	10 Hz to 15.5 kHz
Minimum Resolution Bandwidth	200 Hz
Maximum Resolution Bandwidth	100 kHz
FFT Side Range	32 to 32,768 points
De-emphasis	25, 50, 75 μ s
Total Harmonic Distortion	<0.01%
Signal to Noise Measurement Range	< 80 dB
Signal to Noise Measurement Resolution	0.1 dB
Signal to Noise Measurement Accuracy	+/- 2 dB
Stereo Separation	60 dB

Audio Generator (Internal Source)

Parameter	Specification	Notes
Audio Frequency Range	10 Hz to 15.5 kHz	
Frequency Resolution	1 Hz	
Total Harmonic Distortion	<0.01%	
Stereo Separation	60 dB	
Pilot Signal Frequency	19 kHz (+/- 1Hz)	
Pilot Frequency Deviation	\leq 10 kHz	

Audio Weighting	ITUR 468, C-message, A-weighting, C-weighting	
Number of audio tones	12	Maximum 8 tones in right channel
Minimum tone separation	10 Hz	
Amplitude range	-36 dB to 0 dB	
Pre-emphasis	0, 25, 50, 75 μ s	

RDS / RBDS Specifications

Subcarrier Frequency	57 kHz (+/- 3 Hz)
Frequency Deviation	\leq 10 KHz
Subcarrier Phase	0 or 90 degrees
Number of RDS Groups (TX)	1 (up to 4 blocks)
Number of RDS Groups (RX)	2 (up to 8 blocks)
User Defined Information Bits	\leq 64

FM Measurement Specifications

Measurement	Description	Performance
Signal into Noise and Distortion (SINAD)		< 80 dB
Total Harmonic Distortion + Noise (THD+N)	THD measurement	< 80 dB
Audio Frequency	Audio frequency measurement	<15 kHz (Resolution 500 Hz)
RMS Frequency Deviation	Frequency Deviation (RMS)	< 100 kHz (Resolution 1 Hz), +/- 10%
Peak Frequency Deviation	Frequency Deviation (Peak)	< 100 kHz (Resolution 1 Hz), +/- 10%
Carrier Power Measurement	Average power value of carrier	+/- 2 dB
Power Spectral Density (PSD)	Spectrum of RF signal	+/- 1 MHz
Measurement Resolution	Resolution Bandwidth	1 kHz to 300 kHz
RDS Data Decode	Displays RDS binary data	Up to 2 groups (128 bits)

GPS, GLONASS Hardware Technical Specifications

Parameters	Value
Frequency (GPS)	L1 – 1575.42 MHz (fixed)
Frequency (GLONASS)	L1 – 1598 to 1606 MHz (user settable in 0.5625 MHz steps)
Modulation	BPSK (GPS, GLONASS), CW (no modulation)
Number of simultaneous channels	6 (GPS), 1 (GLONASS)
Simulated signals	1 to 32 selectable (GPS), -7 to +6 (GLONASS)
Output power level	-60 to -145 dBm
Power resolution	0.1dB
Power accuracy *1	-60 to -100 dBm ±0.7dB RSS
-100 to -145 dBm ±1dB RSS	Displays RDS binary data
Frequency accuracy *2	±0.002 ppm / day (±2 x10-9)
GPS Navigation Data	C/A @1.023 MHz with 50 bps
GLONASS Navigation Data	C/A@511 kHz with 50 bps
Carrier + Data Doppler	Frequency offset +/-10.0 kHz with 1 Hz resolution
Transmitted signal quality	Harmonic: < -40dBc Non-Harmonic: < -40 dBc (+/- 10 MHz) 1 deg RMS (1 kHz to 1 MHz SSB)

Near Field Communication (NFC) Hardware Technical Specifications

Analyzer

Channels	2
Voltage Range	5 to 1000 mV RMS (50 Ohm)
Analog Bandwidth	30 MHz
Quantization	14 bits
Sampling Rate	80 MHz
Waveform Capture Duration	400 ms

Generator

Channels	2
Voltage Range	< 1000 mV RMS (50 Ohm)
Analog Bandwidth	35 MHz
Quantization	14 bits

Sampling Rate	80 MHz
Waveform Duration	400 ms

Port Descriptions

Front Panel

I/O	Function	Type
Power Switch	Power on/off	Pushbutton switch
Power Indicator	LED red – powered up, standby LED green – powered up, running	LED indicator
RF port 1	WiFi, WiMAX, Bluetooth	N female
RF Port 2	WiFi, WiMAX, Bluetooth	N female
FM Port	FM TX / RX	N female
GPS, GLONASS Port	GPS, GLONASS TX	N female

Rear Panel

I/O	Function	Type
Trigger 1 input	TTL compatible trigger input	BNC female
Trigger 2 input	TTL compatible trigger output	BNC female
10MHz Ref Input	10MHz reference input	BNC female
Marker Out	TTL compatible trigger output	BNC female
AWG CH1 Out	NFC Signal output 1	BNC female
AWG CH2 Out	NFC Signal output 2	BNC female
DIG CH1 IN	NFC Signal input 1	BNC female
DIG CH2 IN	NFC Signal input 2	BNC female
USB	USB 2.0 compatible connection to external PC Controller	USB type B
AC in	AC power input	100-240VAC (automatically switched) 50 - 60 Hz Includes hard power switch

Physical and Environmental

Dimensions	<p>Measurement in Inches Unit with Handle: 15.5" W x 4" H x 20" D Unit without Handle: 14.7" W x 3.3" H x 17.1" D</p> <p>Measurement in Millimeters Unit with Handle: 393 mm W x 102 mm H x 508 mm D Unit without Handle: 373 mm W x 84 mm H x 434 mm D</p>
Weight	6.8 kg
Power consumption	<300 W
Operating temperature	+10°C to +55°C (IEC EN60068-2-1, 2, 14)
Guaranteed Specification	+20°C to +30°C ambient
Storage temperature	-20°C to +70°C (IEC EN60068-2-1, 2, 14)
Operating humidity	15% to 95% relative humidity, non-condensing (IEC EN60068-2-30)
EMC	EN 61326 Immunity for industrial environment, Class B emissions
Safety	IEC 61010-1, EN61010-1, UL3111-1, CAN/CSA-C22.2 No. 1010.1
Mechanical vibration	IEC 60068, IEC 61010 and MIL-T-28800D, class 5
Mechanical shock	ASTM D3332-99, Method B
Recommended calibration cycle	12 months
Warranty	12 months hardware 12 months software updates

Control PC Minimum Requirements

PC	Intel Pentium dual core processor or compatible, 1GHz (2 GHz or higher recommended)
Operating system	Windows XP (SP2 or higher), US English versions
Memory	1024MB of RAM
Disk space	500MB of available hard disk space
Monitor	1024 x 768 resolution
Connectivity	USB 2.0

Programming Interface and Graphical User Interface (GUI)

Programming Interface and Compatibility

Programmatic interface	C++ API (LitePoint IQapi)
Driver compatibility	C++ LabVIEW 8.5 (using LitePoint supplied driver)

Graphical User Interface (GUI)

IQ 201X Applications	WiFi (802.11) WiMAX (802.16 d/e) GPS, GLONASS FM (TX / RX) Bluetooth (1.0, 2.0, 2.1, 3.0, 4.0) NFC (ISO 18092) ZigBee (802.15.3) WAVE (802.11p)	GUI supports built-in measurement and signal generation functions per standard as appropriate
----------------------	--	---

Ordering Information

Order Code	Description
0100-2015-000	IQ2015 Hardware with WiFi, Bluetooth
0300-20XX-012	IQ20XX GPS / FM License
0300-20XX-001	GPS License
0300-20XX-018	GLONASS License
0300-20XX-002	FM Software Option
0300-20XX-003	Audio Analysis Option Requires 0300-20XX-002 Option Includes LitePoint Audio Interface Module (AiM) Hardware Includes Audio Analysis Software (API and GUI)
0300-20XX-004	NFC Software Option
0300-20XX-005	WiMAX Software Option
0300-ZIGB-001	ZigBee Software Package CD

Copyright © 2014 LitePoint, A Teradyne Company.

All rights reserved

RESTRICTED RIGHTS LEGEND

No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual, or otherwise, without the prior written permission of LitePoint Corporation.

DISCLAIMER

LitePoint Corporation makes no representations or warranties with respect to the contents of this manual or of the associated LitePoint Corporation products, and specifically disclaims any implied warranties of merchantability or fitness for any particular purpose. LitePoint Corporation shall under no circumstances be liable for incidental or consequential damages or related expenses resulting from the use of this product, even if it has been notified of the possibility of such damages.

If you find errors or problems with this documentation, please notify LitePoint Corporation at the address listed below. LitePoint Corporation does not guarantee that this document is error-free. LitePoint Corporation reserves the right to make changes in specifications and other information contained in this document without prior notice.

TRADEMARKS

LitePoint and the LitePoint logo are registered trademarks of LitePoint Corporation. IQ2015 is a trademark of LitePoint Corporation. All other trademarks or registered trademarks are owned by their respective owners

CONTACT INFORMATION

LitePoint Corporation
965 W. Maude Ave.
Sunnyvale, CA 94085-2803
United States of America

Telephone: +1.408.456.5000
Facsimile: +1.408.456.0106

LITEPOINT TECHNICAL SUPPORT

www.litepoint.com/support
Telephone: +1.408.456.5000
Available: weekdays 8am to 6pm,
Pacific Standard Time.
E-mail: support@litepoint.com

Doc: 1075-0022-001
March 2014 Rev 3